

# Alcatel One Touch 300 Series Guide



There are three versions of the Alcatel on the market – all of which have a slightly different menu structure to the other. To determine which version you have, simply Press **OK**, then scroll using the **Middle Key** and highlight **Services**. Press **OK**, and if the phone displays the **Configure Menu** use the setup listed below. If the phone starts connecting to WAP, use the setups with either v.2 or v.3 beside them. To differentiate between v.2 and v.3 software, look at the **Browser Menu** after pressing down **#**. The v.3 software does not have a **Parameters** menu.

## Complete Setup

- Press **OK**, then scroll using the **Middle Key** and highlight **Services**.
- Press **OK** and the **Configure Menu** will now appear.
- Highlight **Your Number** and press **OK**. This will display your mobile number. If this is not the same as the SIMcard in the phone, change it to the correct one. After this has been set correctly, press **OK**.

NB: To set **Your Number**, press and hold **C** key to return to the main menu. Press **OK**, then **OK** again to enter the Menu. Scroll to **Numbers**, then press **OK**. Select **Your Number** by pressing **OK** and enter your mobile in standard format – i.e. **021xxxxxx** – if written in any other format the phone will NOT connect. Press **OK** once you have entered the mobile number. Press and hold the **C** key and follow the above steps over again.

- Scroll down to **Proxy Address** press **OK**. Then enter **172.030.038.003** and press **OK** twice (the dots will be entered automatically.)
- Scroll down to **Proxy Port** then press **OK**. Then enter **9201** and press **OK** twice.
- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted press **OK**.
- **Access 1** will be highlighted press **OK**.
- **RAS number** will appear on your screen. Enter **+6421700747** then press **OK** twice.

NB: To enter a plus, press the **Address Book** key and select **Alpha**, then press zero. Repeat the process to enter numbers but the second time select **Numerical**.

- **Access Type** will appear and **V32** will be highlighted select this by pressing **OK**.
- **Your Choice Has Been Taken Into Account** will appear on your screen.
- Press the **C** key to take you back to **Connect Param**.
- Scroll down to **Username** press **OK**. Then enter **voda** and press **OK** twice.
- Scroll down to **Password** press **OK**. Enter **fone** and press **OK** twice this will bring you back to **Connect Param**.
- Press the **C** key once to take you back to **Configure Menu**.

Scroll to **Homepage** press **OK** twice. Enter **http://wap.vodafone.co.nz/**

Use the following table for entering in the symbols for the homepage:

:	1 seven times
.	0 three times
/	0 six times
?	1 six times
=	* twice, then 1 four times

- Scroll down to **Validate** and press **OK**.

### **Connecting to WAP**

- Press **OK**, then scroll using the **Middle Key** and highlight **Services**.
- Press **OK** and hold down the **#** key.
- Scroll to **Homepage** and press **OK** to connect.

### **Overseas WAP**

- Press **OK**, then scroll using the **Middle Key** and highlight **Services**.
- Press **OK** and the **Configure Menu** will now appear.
- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted, to continue press **OK**.
- **Access 1** will be highlighted, to continue press **OK**.
- **RAS number** will appear on your screen. Make sure that the number is **+6421700747** then press **OK**.
- **Access Type** highlight and choose **UDI** by pressing **OK**.

### **Complete Setup v.2**

NB: The phone will not connect to WAP if the setting **Your Number** is not set correctly. To set **Your Number**, press and hold **C** key to return to the main menu. Press **OK**, then **OK** again to enter the Menu. Scroll to **Numbers**, then press **OK**. Select **Your Number** by pressing **OK** and enter your mobile in standard format – i.e. **021xxxxxx** – if written in any other format the phone will NOT connect. Press **OK** once you have entered the mobile number. Press and hold the **C** key and follow the above steps over again.

NB: To edit any of the parameters mentioned below, scroll through the setting first using the **Middle Key** then use the **C** key to delete any settings already entered.

- Press **OK**, then scroll using the **Middle Key** and scroll up to the **Services** menu.
- Press **OK**, then press and hold the **#** key.
- Scroll down to **Parameters** and press **OK** twice (make sure to select the **Vodafone** profile if available.)
- This will bring up the **Config Menu**.
- Scroll down to **Proxy Address** press **OK**. Then enter **172.030.038.003** and press **OK** twice (the dots will be entered automatically.)
- Scroll down to **Proxy Port** then press **OK**. Then enter **9201** and press **OK** twice.

- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted - press **OK**.
- **Access 1** will be highlighted press **OK**.
- **RAS number** will appear on your screen. Enter **+6421700747** then press **OK** twice.

NB: To enter a plus, press the **Address Book** key and select **Alpha**, then press zero. Repeat the process to enter numbers but the second time select **Numerical**.

- **Access Type** will appear and **V32** will be highlighted select this by pressing **OK**.
- Press the **C** key to take you back to **Connect Param**.
- Scroll down to **Username** press **OK**. Then enter **voda** and press **OK** twice.
- Scroll down to **Password** press **OK**. Enter **fone** and press **OK** twice, reenter **fone** again and press **OK** twice. This will bring you back to **Connect Param**.
- Press the **C** key once to take you back to **Configure Menu**.
- Scroll to **Homepage** press **OK** twice. Enter **http://wap.vodafone.co.nz/** and press **OK**.

Use the following table for entering in the symbols for the homepage:

:	1 seven times
.	0 three times
/	0 six times
?	1 six times
=	* twice, then 1 four times

- Scroll down to **Validate** and press **OK**.

### **Connecting to WAP v.2**

- Press **OK**, then scroll using the **Middle Key** and highlight the **Services** menu, then press **OK**.

### **Overseas WAP v.2**

- Press **OK**, then scroll using the **Middle Key** and scroll up twice to the **Services** menu.
- Press **OK**, then press and hold the **#** key.
- Scroll down to **Parameters** and press **OK**.
- Highlight **Vodafone** and press **OK** twice – this will bring up the **Config Menu**.
- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted, to continue press **OK**.
- **Access 1** will be highlighted, to continue press **OK**.
- **RAS number** will appear on your screen. Make sure that the number is **+6421700747** then press **OK**.

NB: To enter a plus, press the **Address Book** key and select **Alpha**, then press zero. Repeat the process to enter numbers but the second time select **Numerical**.

- Highlight **Access Type** and choose **UDI** by pressing **OK**.

### **Complete Setup v.3**

NB: The phone will not connect to WAP if the setting **Your Number** is not set correctly. To set **Your Number**, press and hold **C** key to return to the main menu. Press **OK**, then **OK** again to enter the Menu. Scroll to **Numbers**, then press **OK**. Select **Your Number** by pressing **OK** and enter your mobile in standard format – i.e. **021xxxxxx** – if written in any other format the phone will NOT connect. Press **OK** once you have entered the mobile number. Press and hold the **C** key and follow the above steps over again.

NB: To edit any of the parameters mentioned below, scroll through the setting first using the **Middle Key** then use the **C** key to delete any settings already entered.

- Press **OK**, then scroll using the **Middle Key** and scroll up to the **Services** menu.
- Press **OK**, then press and hold the **#** key.
- Scroll down to **Configure Menu** and press **OK**.
- Scroll down to **Proxy Address** press **OK**. Then enter **172.030.038.003** and press **OK** (the dots will be entered automatically.)
- Scroll down to **Proxy Port** then press **OK**. Then enter **9201** and press **OK**.
- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted - press **OK**.
- **Access 1** will be highlighted press **OK**.
- **RAS number** will appear on your screen. Enter **+6421700747** then press **OK** twice.

NB: To enter a plus, press the **Address Book** key and select **Alpha**, then press zero. Repeat the process to enter numbers but the second time select **Numerical**.

- **Access Type** will appear and **V32** will be highlighted select this by pressing **OK**.
- Press the **C** key to take you back to **Connect Param**.
- Scroll down to **Login** and press **OK**. Then enter **voda** and press **OK** twice.
- Scroll down to **Password** press **OK**. Enter **fone** and press **OK** twice. This will bring you back to **Connect Param**.
- Press the **C** key once to take you back to **Configure Menu**.
- Scroll to **Homepage** press **OK** twice. Enter **http://wap.vodafone.co.nz/** and press **OK**.

Use the following table for entering in the symbols for the homepage:

:	1 seven times
.	0 three times
/	0 six times
?	1 six times
=	* twice, then 1 four times

- Scroll down to **Validate** and press **OK**.

### **Connecting to WAP v.3**

- Press **OK**, then scroll using the **Middle Key** and highlight the **Services** menu, then press **OK**.

### **Overseas WAP v.3**

- Press **OK**, then scroll using the **Middle Key** and scroll up twice to the **Services** menu.
- Press **OK**, then press and hold the **#** key.
- Scroll down to **Configure Menu** and press **OK**.
- Scroll down and select **Connect Param** by pressing **OK**.
- **Access Mode** will be highlighted, to continue press **OK**.
- **Access 1** will be highlighted, to continue press **OK**.
- **RAS number** will appear on your screen. Make sure that the number is **+6421700747** then press **OK** twice.

NB: To enter a plus, press the **Address Book** key and select **Alpha**, then press zero. Repeat the process to enter numbers but the second time select **Numerical**.

- Highlight **Access Type** and choose **UDI** by pressing **OK**.

### **Disconnecting from WAP**

- Simply hold down the **C** Key at any point while connected to WAP and you will be taken back to the main screen.