

# Motorola V525

## Setup guide



For help or assistance please contact us.

In New Zealand, phone 777 free from your mobile or 0800 800 021

Phone +64 9 357 5198 from Overseas (except Australia)

Phone, toll free, +800 777 000 21 from Australia

Or visit [www.vodafone.co.nz](http://www.vodafone.co.nz)

## Setting GPRS Access Point

Please remember to switch your phone off and back on again after you have changed any settings in the phone.

- Press down the middle button with four lines on it to enter the menu structure.
- Scroll to **Vodafone Live** and press **Select**.
- Scroll down to **Web Sessions** and press **Select**.
- Highlight **[New Entry]** and press **Select**.
- Highlight **Name:** and press **Change**. Enter **VFNZ GPRS** and press **OK**.
- Scroll down to **Home Page:** and press **Change**.
- Enter **http://wap.vodafone.co.nz** and press **OK**.
- Scroll down to **Gateway IP:** and press **Change**.
- Enter **172.030.038.003** and press **OK**.
- Scroll down to **Port 1:** and press **Change**.
- Enter **9201** and press **OK**.
- Scroll to **Service type1** and select **WAP**.
- Scroll down to **Gateway IP 2:** and press **Change**.
- Enter **172.030.038.003** and press **OK**.
- Scroll down to **WAP Port 2:** and press **Change**.
- Enter **9201** and press **OK**.
- Scroll to **Service type 2** and select **WAP**.
- Scroll down to **GPRS APN** and press **Change**.
- Enter **live.vodafone.com** and press **OK**.
- Select **Done**.
- Scroll to the profile you just configured and press the menu key.
- Select **set default**.

## Setting up WAP CSD Access

- Press down the middle button with four lines on it to enter the menu structure.
- Scroll to **Vodafone Live** and press **Select**.
- Scroll down to **Web Sessions** and press **Select**.
- Highlight **[New Entry]** and press **Select**.
- Highlight **Name:** and press **Change**. Enter **VFNZ CSD** and press **OK**.
- Scroll down to **Home Page:** and press **Change**.
- Enter **http://wap.vodafone.co.nz** and press **OK**.
- Scroll down to **Gateway IP:** and press **Change**.
- Enter **172.030.038.003** and press **OK**.
- Scroll down to **Port 1:** and press **Change**.
- Enter **9201** and press **OK**.
- Scroll down to **Gateway IP 2:** and press **Change**.
- Enter **172.030.038.003** and press **OK**.
- Scroll down to **Port 2:** and press **Change**.
- Enter **9201** and press **OK**.
- Scroll down to **Timeout:** and press **Change**.
- Scroll to **1 minute** and press **Select**.
- Scroll down to **CSD No. 1:** and press **Change**.
- Enter the number **+6421700747** and press **OK**.
- Scroll down to **User Name 1:** should be blank.
- Scroll down to **Password 1:** should be blank.
- Scroll down to **Speed (Bps) 1:** and press **Change**.
- Scroll **14400** and press **Select**.
- Scroll down to **Line Type 1:** and press **Change**.
- Scroll to **ISDN** and press **Select**.
- Scroll down to **Line Type 2:** and press **Change**.
- Scroll to **ISDN** and press **Select**.
- Press **Done**.

## 2 CONFIGURING THE MOTOROLA V525 FOR PXT



### Setting up PXT access

- Select **Message** from the main screen of your phone.
- Press the **Menu** button and scroll to **Message setup** and press **Select**.
  - Scroll to **MMS Msg Setup**. Press **Change**
  - Scroll to **Server info** and select **Select**
  - Press the menu key and select **New**
  - Scroll to **Service name** and press **Change**
  - Enter **VFNZ PXT** and press **OK**.
  - Scroll to **Server Name** and press **Change**.
  - Enter <http://pxt.vodafone.net.nz/pxtsend> and press **OK**.
  - Scroll to **Web session name** and press **change**.
  - Select **VFNZ GPRS** and press **Select**.
  - Press **Done**.
  - Scroll to the profile you just created and press **Select**.

## 3 CONFIGURING THE MOTOROLA V525 FOR EMAIL CLIENT.



### Setting up email access

- Select **Message** from the main screen of your phone.
- Press the **Menu** button and scroll to **Email Message Setup** and press **Select**.
  - Scroll to **ISP setting**. Press **Change**
  - Scroll to **Connection type**. Press **Change**.
  - Scroll to **GPRS**. Press **Select**.
  - Scroll to **APN address**. Press **Change**.
  - Enter [www.vodafone.net.nz](http://www.vodafone.net.nz) press **OK**.**(Leave Username, Password and DNS IP blank)**
  - Click on **Done**
  - Scroll to **Protocol** and press **Change**
  - Scroll to **POP3** and press **Select**
  - Scroll to **User ID** and press **Change**
  - Type in the User ID for your Internet Service Provider and press **OK**
  - Scroll to **Password** and press **Change**
  - Type in password for your Internet Service Provider and press **OK**
  - Type in password again and press **OK**
  - Scroll to **Sending Host** and press **Change**
  - Type in [smtp.vodafone.net.nz](mailto:smtp.vodafone.net.nz) and press **OK**
  - Scroll to **Receiving host** and press **Change**.
  - Enter the POP address for your email provider. Call your email provider if you are not aware of the POP address.
  - Scroll to **Return address** and enter your email address.
  - Scroll to **Name** and enter the name you want to be displayed on emails sent from your phone.
  - Scroll to **Save on server** and press **Change**. Select **Yes**.
  - Scroll to **Check new msgs** and press **Change**. Select **No**.
  - Press **Done**.